



## LED security light INTELIGHT LTR-25 8W 230V 8W

Product code 19605

The heating element is designed for use with ORION and VELLA series emergency lights, which are permanently located at temperatures between + 10° C and -25° C.

Activates when the temperature is below + 3° C and deactivates when it reaches + 10° C.

Approved for use with: NiCd, NiMH and LiFePO4 batteries

Standby: Uses less than 1W

Operating Mode: Uses a maximum of 15W

The warranty applies if the heating element is used inside an ORION or VELLA series luminaire.

Warranty	1 years
Brand	<a href="#">INTELIGHT</a>
Supply voltage	230V
Output	8W
Maximum output	8W
In package	1pc
Operation temperature	kuni -25°C
Certificates	CE,RoHS

