




## Dimmer SKYDANCE S1-D 2 tsooni 200W DMX / TRIAC

Tootekood 15943

Kahe tsooniga 100W LED 200W halogeen/hõõglamp triac dimmer DMX juhtimisega.

Bränd [SKYDANCE](#)  
 Hämardatav DMX / TRIAC  
 Võimsus 200W  
 Pakis 1tk  
 Korpuse materjal plastik  
 Poleer matt



### Compatible Load Types

| Load Type                              | Maximum load               | Remarks   |
|--|----------------------------|---|
| Dimmable LED lamps                     | 100W @ 220V<br>200W @ 110V | Due to variety of LED lamp design, maximum number of LED lamps is further dependent on power factor and other characteristics of dimmer.                      |
| Triac Dimmable LED drivers             | 100W @ 220V<br>200W @ 110V | Maximum permitted number of drivers is 100W divided by driver maximum power rating, and make sure the surge current is no more than 2 times I <sub>MA</sub> . |
| Incandescent lighting or halogen lamps | 200W @ 220V<br>100W @ 110V |   |

### Wiring Diagram

**Caution:** Please carefully ensure all wire connections and polarities are correct and accurate before applying power, otherwise the controller will be damaged.

• Connect with dimmable LED light

