




Himmennin SKYDANCE Triac Dimmer S1-D 200W

Tuotekoodi 15943

Brändi [SKYDANCE](#)
 Himmennettävä DMX
 Teho 200W
 Paketissa 1kpl
 Rungon materiaali muovi
 Kiilto matto



Mechanical Structures and Installations



Compatible Load Types

Load Type	Maximum load	Remarks
Dimmable LED lamps	100W @ 220V 200W @ 110V	Due to variety of LED lamp designs, maximum number of LED lamps is further dependent on power factor and when connected to dimmer.
Non-Dimmable LED driver	100W @ 220V 200W @ 110V	Maximum permitted number of drivers is 100W divided by driver nominal power rating, and make sure the surge current is no more than 2 times IQR.
Incandescent lighting HV Fluorescent lamps	200W @ 220V 100W @ 110V	

Wiring Diagram

Caution: Please carefully check all wire connections and polarities are correct and secure before applying power, otherwise this controller will be damaged.

• Connect with dimmable LED light

